

DIODOS ZENER

Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
	(Watts)		(mA)		
1N762A	0.25	5.8	10	DO-7	A
1N4371A	0.4	2.7	20	DO-7	A
1N4372A	0.4	3	20	DO-7	A
1N746A	0.4	3.3	20	DO-35	Q
1N747A	0.4	3.6	20	DO-35	Q
1N748A	0.4	3.9	20	DO-35	Q
1N749A	0.4	4.3	20	DO-35	Q
1N750A	0.4	4.7	20	DO-35	Q
1N751A	0.4	5.1	20	DO-35	Q
1N752A	0.4	5.6	20	DO-35	Q
1N753A	0.4	6.2	20	DO-35	Q
1N754A	0.4	6.8	20	DO-35	Q
1N755A	0.4	7.5	20	DO-35	Q
1N756A	0.4	8.2	20	DO-35	Q
1N757A	0.4	9.1	20	DO-35	Q
1N758A	0.4	10	20	DO-35	Q
1N962B	0.4	11	11.5	DO-35	Q
1N759A	0.4	12	20	DO-35	Q
1N965B	0.4	15	8.5	DO-35	Q
1N966B	0.4	16	7.8	DO-35	Q
1N967B	0.4	18	7	DO-35	Q
1N968B	0.4	20	6.2	DO-35	Q
1N969B	0.4	22	5.6	DO-35	Q
1N970B	0.4	24	5.2	DO-35	Q
1N971B	0.4	27	4.6	DO-35	Q
1N972B	0.4	30	4.2	DO-35	Q
1N973B	0.4	33	3.8	DO-35	Q
1N4728A	1	3.3	76	DO-41	A
1N4729A	1	3.6	69	DO-41	A
1N4730A	1	3.9	64	DO-41	A
1N4731A	1	4.3	58	DO-41	A
1N4732A	1	4.7	53	DO-41	A
1N4733A	1	5.1	49	DO-41	A
1N4734A	1	5.6	45	DO-41	A
1N4735A	1	6.2	41	DO-41	A
1N4736A	1	6.8	37	DO-41	A
1N4737A	1	7.5	34	DO-41	A
1N4738A	1	8.2	31	DO-41	A
1N4739A	1	9.1	28	DO-41	A
1N4740A	1	10	25	DO-41	A
1N4741A	1	11	23	DO-41	A

Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
1N4742A	1	12	21	DO-41	A
1N4743A	1	13	19	DO-41	A
1N4744A	1	15	17	DO-41	A
1N4745A	1	16	15.5	DO-41	A
1N4746A	1	18	14	DO-41	A
1N4747A	1	20	12.5	DO-41	A
1N4748A	1	22	11.5	DO-41	A
1N4749A	1	24	11	DO-41	A
1N4750A	1	27	9.5	DO-41	A
1N4751A	1	30	8.5	DO-41	A
1N4752A	1	33	7.5	DO-41	A
1N4753A	1	36	7	DO-41	A
1N4754A	1	39	6.5	DO-41	A
1N4755A	1	43	6	DO-41	A
1N4756A	1	47	5.5	DO-41	A
1N4757A	1	51	5	DO-41	A
1N4758A	1	56	4.5	DO-41	A
1N4759A	1	62	4	DO-41	A
1N4760A	1	68	3.7	DO-41	A
1N4761A	1	75	3.3	DO-41	A
1N4762A	1	82	3	DO-41	A
1N4763A	1	91	2.8	DO-41	A
1N4764A	1	100	2.5	DO-41	A
1EZ110	1	110	2.3	DO-41	A
1EZ150	1	150	1.7	DO-41	A
1EZ180	1	180	1.4	DO-41	A
1EZ200	1	200	1.2	DO-41	A
1N5333	5	3.3	380	AXIAL	C
1N5334	5	3.6	350	AXIAL	C
1N5335	5	3.9	320	AXIAL	C
1N5336	5	4.3	290	AXIAL	C
1N5337	5	4.7	260	AXIAL	C
1N5338	5	5.1	240	AXIAL	C
1N5339	5	5.6	220	AXIAL	C
1N5340	5	6	200	AXIAL	C
1N5341	5	6.2	200	AXIAL	C
1N5342	5	6.8	175	AXIAL	C
1N5343	5	7.5	175	AXIAL	C
1N5344	5	8.2	150	AXIAL	C
1N5346	5	9.1	150	AXIAL	C
1N5347	5	10	125	AXIAL	C
1N5348	5	11	125	AXIAL	C
1N5349	5	12	100	AXIAL	C

Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
1N5350	5	13	100	AXIAL	C
1N5352	5	15	75	AXIAL	C
1N5353	5	16	75	AXIAL	C
1N5355	5	18	65	AXIAL	C
1N5357	5	20	65	AXIAL	C
1N5358	5	22	50	AXIAL	C
1N5359	5	24	50	AXIAL	C
1N5361	5	27	50	AXIAL	C
1N5362	5	28	50	AXIAL	C
1N5363	5	30	40	AXIAL	C
1N5364	5	33	40	AXIAL	C
1N5365	5	36	30	AXIAL	C
1N5366	5	39	30	AXIAL	C
1N5367	5	43	30	AXIAL	C
1N5368	5	47	25	AXIAL	C
1N5369	5	51	25	AXIAL	C
1N5370	5	56	20	AXIAL	C
1N5371	5	60	20	AXIAL	C
1N5372	5	62	20	AXIAL	C
1N5373	5	68	20	AXIAL	C
1N5374	5	75	20	AXIAL	C
1N5375	5	82	15	AXIAL	C
1N5376	5	87	15	AXIAL	C
1N5377	5	91	15	AXIAL	C
1N5378	5	100	12	AXIAL	C
1N5379	5	110	12	AXIAL	C
1N5380	5	120	10	AXIAL	C
1N5381	5	130	10	AXIAL	C
1N5383	5	150	8	AXIAL	C
1N5384	5	160	8	AXIAL	C
1N5386	5	180	5	AXIAL	C
1N5388	5	200	5	AXIAL	C
1N3993A*	10	3.9	640	DO-4	I
1N3993RA	10	3.9	640	DO-4	I
1N3994A*	10	4.3	580	DO-4	I
1N3995A*	10	4.7	530	DO-4	I
1N3996A*	10	5.1	490	DO-4	I
1N3997A*	10	5.6	445	DO-4	I
1N3997RA	10	5.6	445	DO-4	I
1N3998RA	10	6.2	405	DO-4	I
1N2970B	10	6.8	370	DO-4	I
1N2970RB	10	6.8	0.37	DO-4	I
1N2971B	10	7.5	335	DO-4	I

Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
1N2971RB*	10	7.5	335	DO-4	I
1N2972B	10	8.2	305	DO-4	I
1N2972RB*	10	8.2	305	DO-4	I
1N2973B	10	9.1	275	DO-4	I
1N2973RB*	10	9.1	275	DO-4	I
1N2974B	10	10	250	DO-4	I
1N2974RB*	10	10	250	DO-4	I
1N2975B	10	11	230	DO-4	I
1N2975RB*	10	11	230	DO-4	I
1N2976B	10	12	210	DO-4	I
1N2976RB*	10	12	210	DO-4	I
1N2977B	10	13	190	DO-4	I
1N2977RB*	10	13	190	DO-4	I
1N2978B	10	14	180	DO-4	I
1N2978RB*	10	14	180	DO-4	I
1N2979B	10	15	170	DO-4	I
1N2979RB*	10	15	170	DO-4	I
1N2980B	10	16	155	DO-4	I
1N2980RB*	10	16	155	DO-4	I
1N2981B	10	17	145	DO-4	I
1N2981RB*	10	17	145	DO-4	I
1N2982B	10	18	140	DO-4	I
1N2982RB*	10	18	140	DO-4	I
1N2984B	10	20	125	DO-4	I
1N2984RB*	10	20	125	DO-4	I
1N2985B	10	22	115	DO-4	I
1N2985RB*	10	22	115	DO-4	I
1N2986B	10	24	105	DO-4	I
1N2986RB*	10	24	105	DO-4	I
1N2988B	10	27	95	DO-4	I
1N2988RB*	10	27	95	DO-4	I
1N2989B	10	30	85	DO-4	I
1N2989RB*	10	30	85	DO-4	I
1N2990B	10	33	85	DO-4	I
1N2990RB*	10	33	85	DO-4	I
1N2991B	10	36	70	DO-4	I
1N2991RB*	10	36	70	DO-4	I
1N2992B	10	39	65	DO-4	I
1N2992RB*	10	39	65	DO-4	I
1N2993B	10	43	60	DO-4	I
1N2993RB*	10	43	60	DO-4	I
1N2994B	10	45	55	DO-4	I
1N2994RB*	10	45	55	DO-4	I

Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
1N2995B	10	47	55	DO-4	I
1N2995RB*	10	47	55	DO-4	I
1N2996B	10	50	50	DO-4	I
1N2996RB*	10	50	50	DO-4	I
1N2997B	10	51	50	DO-4	I
1N2997RB*	10	51	50	DO-4	I
1N2998B	10	52	50	DO-4	I
1N2998RB*	10	52	50	DO-4	I
1N2999B	10	56	45	DO-4	I
1N2999RB*	10	56	45	DO-4	I
1N3000B	10	62	40	DO-4	I
1N3000RB*	10	62	40	DO-4	I
1N3001B	10	68	37	DO-4	I
1N3001RB*	10	68	37	DO-4	I
1N3002B	10	75	33	DO-4	I
1N3002RB*	10	75	33	DO-4	I
1N3003B	10	82	30	DO-4	I
1N3003RB*	10	82	30	DO-4	I
1N3004B	10	91	28	DO-4	I
1N3004RB*	10	91	28	DO-4	I
1N3005B	10	100	25	DO-4	I
1N3005RB*	10	100	25	DO-4	I
1N3006B	10	105	25	DO-4	I
1N3006RB*	10	105	25	DO-4	I
1N3007B	10	110	23	DO-4	I
1N3007RB*	10	110	23	DO-4	I
1N3009B	10	130	19	DO-4	I
1N3009RB*	10	130	19	DO-4	I
1N3011B	10	150	17	DO-4	I
1N3011RB*	10	150	17	DO-4	I
1N3013B	10	175	14	DO-4	I
1N3013RB*	10	175	14	DO-4	I
1N3014B	10	180	14	DO-4	I
1N3014RB*	10	180	14	DO-4	I
1N3015B	10	200	12	DO-4	I
1N3015RB*	10	200	12	DO-4	I
1N4557	50	3.9	3200	TO-3	K
1N4559	50	4.7	2650	TO-3	K
1N4560	50	5.1	2450	TO-3	K
1N4561	50	5.6	2250	TO-3	K
1N3305	50	6.8	1850	DO-5	G
1N3306	50	7.5	1700	DO-5	G
1N3307	50	8.2	1500	DO-5	G


Código	Potencia	Tensión Vz (Volts)	I _{ZT}	Encapsulado	Figura
1N3308	50	9.1	1370	DO-5	G
1N3309	50	10	1200	DO-5	G
1N3310	50	11	1100	DO-5	G
1N3311	50	12	1000	DO-5	G
1N3312	50	13	960	DO-5	G
1N3314	50	15	830	DO-5	G
1N3315	50	16	780	DO-5	G
1N3317	50	18	700	DO-5	G
1N3318	50	19	660	DO-5	G
1N3319	50	20	630	DO-5	G
1N3320	50	22	570	DO-5	G
1N3321	50	24	520	DO-5	G
1N3323	50	27	460	DO-5	G
1N3324	50	30	420	DO-5	G
1N3325	50	33	380	DO-5	G
1N3326	50	36	350	DO-5	G
1N3327	50	39	320	DO-5	G
1N3328	50	43	290	DO-5	G
1N3330	50	47	270	DO-5	G
1N3332	50	51	245	DO-5	G
1N3334	50	56	220	DO-5	G
1N3335	50	62	200	DO-5	G
1N3336	50	68	180	DO-5	G
1N3337	50	75	170	DO-5	G
1N3339	50	91	140	DO-5	G
1N3340	50	100	120	DO-5	G
1N3342	50	110	110	DO-5	G
1N3344	50	130	95	DO-5	G
1N3346	50	150	85	DO-5	G
1N3347	50	160	80	DO-5	G
1N3348	50	175	70	DO-5	G
1N3350	50	200	65	DO-5	G

* CATODO A TORNILLO

DIODOS: RECTIFICADORES, RAPIDOS, ALTA TENSION, SCHOTTKY Y ZENER


ENCAPSULADOS Y FIGURAS

FIGURA A




DO-41

FIGURA B



DO-201

FIGURA C



AXIAL

FIGURA D




TO-251

FIGURA E



TO-220

FIGURA F




TO-3P

FIGURA G



DO-5

FIGURA H



DO-27

FIGURA I



DO-4

FIGURA J



D-8A

CONTINUA EN HOJA SIGUIENTE

DIODOS: RECTIFICADORES, RAPIDOS, ALTA TENSION, SCHOTTKY Y ZENER

CONTINUACION

ENCAPSULADOS Y FIGURAS

